

Technical Parameters Power Amplifier **RL-A500**

Max. output power (RMS)	500 VA
Frequency range	DC-20 kHz
Voltage, max. (RMS)	44 V
Current, max. (RMS)	11.5 A
Signal input voltage (RMS)	3 V
Distortion	<0.2%
Signal-to-noise ratio	>80 dB
Weight	5.6
Dimensions (WxHxD)	390x80x290
Power supply	1~/N/PE 180-240 V, 50-60 Hz
Max. power consumption at 230 V (full load)	800 VA
Interlocks	Overload, short circuit, overheat

Features:

- RULA Power Amplifiers can be adapted to all permanent magnet driven shakers on the market
- Digital gain control
- Adjustable current limit
- Multifunctional LCD
- Safety management system monitors such functions as temperature, overcurrent, overvoltage

